

Part Number: 6578130121

78 EP CORE SET

**EP designs reduce the effect of residual air gap upon the effective permeability of the core, hence they minimize coil volume for a given inductance. EP cores also provide a high degree of isolation from adjacent components and are advantageously used in low power devices, matching and broadband transformers.**


□EP cores can be supplied with the center post gapped to a mechanical dimension or an  $A_L$  value.

[Catalog Drawing](#)  
[3D Model](#)

Weight indicates is per pair or set.

Weight: 2.35 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	12.5	$\pm 0.30$	0.492	—
B	6.5	$\pm 0.30$	0.256	—
C	8.8	$\pm 0.20$	0.346	—
D	4.7	$\pm 0.20$	0.185	—
E	10	$\pm 0.30$	0.394	—
F	4.4	$\pm 0.20$	0.173	—
K	2.5	min	0.098	—



## Chart Legend

$\Sigma l/A$  : Core Constant,  $l_e$  : Effective Path Length,  $A_e$  : Effective Cross-Sectional Area,  $V_e$  : Effective Core Volume

$A_L$  : Inductance Factor 

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties	
$A_L$ (nH)	1600 $\pm 25\%$
$A_e$ (cm <sup>2</sup> )	0.197
$\Sigma l/A$ (cm <sup>-1</sup> )	11.8

Electrical Properties	
$l_e(\text{cm})$	2.32
$V_e(\text{cm}^3)$	0.457
$A_{\min}(\text{cm}^2)$	0.148

$A_L$  value is measured at 1 kHz,  $B < 10$  gauss

Fair-Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288  
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • [ferrites@fair-rite.com](mailto:ferrites@fair-rite.com) • [www.fair-rite.com](http://www.fair-rite.com)