

Part Number: 6595100121

95 EP CORE SET


**EP designs reduce the effect of residual air gap upon the effective permeability of the core, hence they minimize coil volume for a given inductance. EP cores also provide a high degree of isolation from adjacent components and are advantageously used in low power devices, matching and broadband transformers.**

□EP cores can be supplied with the center post gapped to a mechanical dimension or an  $A_L$  value.

Weight indicates is per pair or set.

Weight: 1.4 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	11.5	± 0.30	0.453	-
B	5.1	± 0.20	0.201	-
C	7.7	± 0.20	0.303	-
D	3.8	± 0.20	0.15	-
E	9.4	± 0.20	0.37	-
F	3.3	± 0.20	0.13	-
K	1.95	min	0.076	-



### Chart Legend

$\Sigma l/A$  : Core Constant,  $l_e$  : Effective Path Length,  $A_e$  : Effective Cross-Sectional Area,  $V_e$  : Effective Core Volume

$A_L$  : Inductance Factor 

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties	
$A_L$ (nH)	1200 ±25%
$A_e$ (cm <sup>2</sup> )	0.11
$\Sigma l/A$ (cm <sup>-1</sup> )	16.8
$l_e$ (cm)	1.85
$V_e$ (cm <sup>3</sup> )	0.203

Electrical Properties	
$A_{\min}(\text{cm}^2)$	0.085

$A_L$  value is measured at 1 kHz,  $B < 10$  gauss

Fair-Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288  
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • [ferrites@fair-rite.com](mailto:ferrites@fair-rite.com) • [www.fair-rite.com](http://www.fair-rite.com)