

Part Number: 6578100121

78 EP CORE SET

EP designs reduce the effect of residual air gap upon the effective permeability of the core, hence they minimize coil volume for a given inductance. EP cores also provide a high degree of isolation from adjacent components and are advantageously used in low power devices, matching and broadband transformers.

□EP cores can be supplied with the center post gapped to a mechanical dimension or an A_L value.

[Catalog Drawing](#)
[3D Model](#)

Weight indicates is per pair or set.

Weight: 1.4 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	11.5	± 0.30	0.453	—
B	5.1	± 0.20	0.201	—
C	7.7	± 0.20	0.303	—
D	3.8	± 0.20	0.15	—
E	9.4	± 0.20	0.37	—
F	3.3	± 0.20	0.13	—
K	1.95	min	0.076	—




Chart Legend

$\Sigma l/A$: Core Constant, l_e : Effective Path Length, A_e : Effective Cross-Sectional Area, V_e : Effective Core Volume

A_L : Inductance Factor 

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties	
A_L (nH)	1000 $\pm 25\%$
A_e (cm ²)	0.11
$\Sigma l/A$ (cm ⁻¹)	16.8

Electrical Properties	
$l_e(\text{cm})$	1.85
$V_e(\text{cm}^3)$	0.203
$A_{\min}(\text{cm}^2)$	0.085

A_L value is measured at 1 kHz, $B < 10$ gauss

Fair-Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • ferrites@fair-rite.com • www.fair-rite.com