

Part Number: 9578494902

78 ETD CORE SET

ETD cores have been designed to make optimum use of a given volume of ferrite material for maximum throughput power, specifically for forward converter transformers. The structure, which includes a round center post, approaches a nearly uniform cross-sectional area throughout the core and provides a winding area that minimizes winding losses. ETD cores are used mainly in switched-mode power supplies and permit off-line designs where IEC and VDE isolation requirements must be met.

□ETD cores can be supplied with the center post gapped to a mechanical dimension or an  $A_L$  value.


[Catalog Drawing](#)

[3D Model](#)

Weight indicated is per pair or set.

Weight: 124 (g)

Dim	mm	mm tol	nominal inch	inch misc.
A	49	± 0.80	1.929	—
B	24.7	± 0.20	0.972	—
C	16.3	± 0.40	0.642	—
D	18.1	± 0.20	0.713	—
E	36.1	min	1.422	min
F	16.3	± 0.40	0.642	—



## Chart Legend

$\Sigma l/A$  : Core Constant,  $l_e$  : Effective Path Length,  $A_e$  : Effective Cross-Sectional Area,  $V_e$  : Effective Core Volume

$A_L$  : Inductance Factor 

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

Electrical Properties	
$A_L$ (nH)	4000 ±25%

Electrical Properties	
$A_e(\text{cm}^2)$	2.135
$\Sigma l/A(\text{cm}^{-1})$	5.3
$l_e(\text{cm})$	11.44
$V_e(\text{cm}^3)$	24.42
$A_{\min}(\text{cm}^2)$	2.09

$A_L$  value is measured at 1 kHz,  $B < 10$  gauss

Fair-Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288  
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • [ferrites@fair-rite.com](mailto:ferrites@fair-rite.com) • [www.fair-rite.com](http://www.fair-rite.com)