

Part Number: 9595494902

95 ETD CORE SET

ETD cores have been designed to make optimum use of a given volume of ferrite material for maximum throughput power, specifically for forward converter transformers. The structure, which includes a round center post, approaches a nearly uniform cross-sectional area throughout the core and provides a winding area that minimizes winding losses. ETD cores are used mainly in switched-mode power supplies and permit off-line designs where IEC and VDE isolation requirements must be met.

□ETD cores can be supplied with the center post gapped to a mechanical dimension or an A_L value.

[Catalog Drawing](#)

[3D Model](#)

Weight indicated is per pair or set.

Weight: 124 (g)

| Dim | mm | mm tol | nominal inch | inch misc. |
|-----|------|--------|--------------|------------|
| A | 49 | ± 0.80 | 1.929 | — |
| B | 24.7 | ± 0.20 | 0.972 | — |
| C | 16.3 | ± 0.40 | 0.642 | — |
| D | 18.1 | ± 0.20 | 0.713 | — |
| E | 36.1 | min | 1.422 | min |
| F | 16.3 | ± 0.40 | 0.642 | — |




Chart Legend

$\Sigma l/A$: Core Constant, l_e : Effective Path Length, A_e : Effective Cross-Sectional Area, V_e : Effective Core Volume

A_L : Inductance Factor 

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

| Electrical Properties | |
|-----------------------|-----------|
| A_L (nH) | 5700 ±25% |

| Electrical Properties | |
|------------------------------|-------|
| $A_e(\text{cm}^2)$ | 2.135 |
| $\Sigma l/A(\text{cm}^{-1})$ | 5.3 |
| $l_e(\text{cm})$ | 11.44 |
| $V_e(\text{cm}^3)$ | 24.42 |
| $A_{\min}(\text{cm}^2)$ | 2.09 |

A_L value is measured at 1 kHz, $B < 10$ gauss

Fair-Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • ferrites@fair-rite.com • www.fair-rite.com