

Part Number: 9595343502

95 ETD CORE SET

ETD cores have been designed to make optimum use of a given volume of ferrite material for maximum throughput power, specifically for forward converter transformers. The structure, which includes a round center post, approaches a nearly uniform cross-sectional area throughout the core and provides a winding area that minimizes winding losses. ETD cores are used mainly in switched-mode power supplies and permit off-line designs where IEC and VDE isolation requirements must be met.

□ETD cores can be supplied with the center post gapped to a mechanical dimension or an A_L value.

Weight indicated is per pair or set.

Weight: 40 (g)

| Dim | mm | mm tol | nominal inch | inch misc. |
|-----|------|--------|--------------|------------|
| A | 34.2 | ± 0.65 | 1.346 | - |
| B | 17.3 | ± 0.20 | 0.681 | - |
| C | 10.8 | ± 0.30 | 0.425 | - |
| D | 12.1 | ± 0.20 | 0.476 | - |
| E | 25.6 | min | 1.008 | min |
| F | 10.8 | ± 0.30 | 0.425 | - |




Chart Legend

$\Sigma l/A$: Core Constant, l_e : Effective Path Length, A_e : Effective Cross-Sectional Area, V_e : Effective Core Volume

A_L : Inductance Factor 

Explanation of Part Numbers: Digits 1 & 2 = product class and 3 & 4 = material grade.

| Electrical Properties | |
|----------------------------------|-----------|
| A_L (nH) | 3570 ±25% |
| A_e (cm ²) | 0.972 |
| $\Sigma l/A$ (cm ⁻¹) | 8.2 |
| l_e (cm) | 7.9 |

| Electrical Properties | |
|-------------------------------|-------|
| $V_e(\text{cm}^3)$ | 7.68 |
| $A_{\text{min}}(\text{cm}^2)$ | 0.916 |

A_L value is measured at 1 kHz, $B < 10$ gauss

Fair-Rite Products Corp. • One Commercial Row, Wallkill, New York 12589-0288
888-324-7748 • 845-895-2055 • Fax: 845-895-2629 • ferrites@fair-rite.com • www.fair-rite.com